
Customer: PRINCETON PLASMA PHYSICS LAB

Contact: LARRY SUTTON
E-Mail: S-04286-F

Telephone: 609-243-2441
Fax: 609-243-2021

Part: SE122-149-1A / PORT 4A COVER PLATE ASSEMBLY

Drawing ID: SE122-149

Revision: 0

Customer P.O.: S005243-F/Ln:9

Serial No: 9/128

Reported By: DOUG MCCORKLE

E-Mail: dMcCorkle@MajorTool.com

Telephone: 317-636-6433

Fax: 317-634-9420

Problem: Magnetic Permeability 1.02 Max
Checks between 1.1 and 1.15

Proposed Disposition:

CUSTOMER DISPOSITION REQUIRED

Number of additional pages: _____

Customer Disposition: Use As Is Rework Repair Scrap Replace

Technical Contact Approval: _____

Title: _____ **Date:** _____

Buyer Approval: _____

Title: _____ **Date:** _____

Major Tool Implemented By: _____

Title: _____ **Date:** _____

Nonconformance Report: Major Tool NC19164

This is for **SE122-149-1A / PORT 4A COVER PLATE ASSEMBLY**

Problem:

Magnetic Permeability 1.02 Max

Checks between 1.1 and 1.15

Project Disposition:

Accept as is

Approvals:

Procurement Technical Representative

Art Brooks, Technical Assurance

Responsible Line Manager:

Project Quality Assurance: